



KS-1000M 1000Watt Modified Sine Wave Inverter



- ◆ Power on/off switch
- ◆ USB connection (optimal)
- ◆ Build in high Speed cooling fans
- ◆ LED power / fault indicator
- ◆ Fuse built out
- ◆ Cigarette lighter and battery cables
- ◆ One Years Warranty

Electrical Specifications

Continuous power	1000 watts
Surge capacity (peak)	2000watts
DC Input (optional)	12 V;24VDC
Output wave form	Modified sine wave
AC output frequency(optional)	50HZ/60 Hz
AC output voltage (optional)	220VAC/110 VAC
Optimum efficiency	85%
No load draw	< 0.58 A
Input voltage range	10 - 15.5 VDC;20-30VDC
Over voltage shutdown	15+/-0.5 VDC;31+/-0.5VDC
Low voltage alarm	10.5+/-0.5 VDC;21+/-0.5VDC
Under voltage shutdown	10.0+/-0.5 VDC;21+/-0.5VDC

General Specifications

Working temperature (optimal)	15° C to 25° C (59° F to 77° F)
Working temperature	-20° C to +40° C (-4° F to 104° F)
USB port(optimal)	5VDC, 500mA
LED indicator	Power and fault status

Packing Details

Dimensions (L x W x H)	210 x 150 x 70 mm
Inverter Weight	2.7kgs
Shipping Weight	16.5 kgs
Shipping Size	420x 340 x435 mm
PCS/CTN	6PCS

Application:charge laptops, MP3 players, TVs, blenders and many other appliances and electronics.

Note:(1)Specifications are subject to change without notice

(2)Optional:Factory-Set